



20% larger viewing area than 42" plasma displays. Ideally designed to display SDTV, HDTV and all other DTV signals as well as computer resolutions. Weighing just 82 pounds, this multimedia wonder can easily be mounted to any place you can imagine. And with its wide range of features, this 46" diagonal monitor can be used in home theater settings, classrooms, corporate boardrooms, or any place that clear images and easy functionality are necessary. External speakers, desk stand and wall bracket are optional.

**PD4600 Specifications**

Aspect Ratio:	16:9
Screen size (H x V):	46" diagonal, 36.65" x 22.354" / 100.7 x 56.74cm
Resolution:	852 (h) x 480 (v) pixels
Color Resolution:	16.7 million Colors
Brightness:	700 cd/m ²
Contrast Ratio:	800:1 (without filter)
View angle:	Over 160 degrees
Built-in Speakers:	2 x 2 W
Computer Resolution:	Compatible up to 1024 x 768
Video System:	NTSC / PAL / SECAM
Video Signal:	1080i, 720p, 480p, 480i
Safety Regulation:	FCC(B), UL, C-UL, CE
Dimensions (W x H x D):	44.8" x 29.72" x 10.24" (with stand) / 44.8" x 27.2" x 3.8" (w/o stand)
Packing Dimensions: (W x H x D)	113.8 x 75.5 x 26cm (with stand) / 113.8 x 69.1 x 9.8cm (w/o stand) 55.57" x 33.46" x 13" / 131 x 85 x 33cm
Weight:	105.8lbs. (with stand), 88.2lbs (w/o stand) 48Kg (with stand) / 40Kg (w/o stand)
AC Input:	90~110Vac / 216 ~ 264Vac, 50Hz / 60Hz
Warranty:	1 year parts & labor
CONTROL	
Function Key:	power, input, menu, up/down, left/ right
Specially Function:	Zoom, Freeze, PIP (with PC mode), Wide, WOW (surrounding sound)
OSD Language:	English / Chinese (simplified) / Chinese (Traditional), German, Spanish
INPUTS	
PC Input:	D-sub 15-pin
DVI Input:	30-pin DVI connector
Audio System:	AMP : 10W x 2 (Lever Terminal)
External Speakers:	10W + 10W (Optional)
RS-232C:	D-sub 9-pin
TV Tuner Module	
Component Video In:	RCA x 3 (Y, Cb/Pb, Cr/Pr)
Audio Input 1:	RCA x 2 (R and L) for Component Video and PC
S-Video In:	Mini-Din 4-pin
Composite Video In:	RCA x 1
Audio Input 2:	RCA x 2 (R and L) for Composite Video and S-VHS video
Composite Video Out:	BNC x 1
Tuner:	Coaxial Connector for CableTV or Antenna (NTSC)